

AMPLIFIERS

P3-35 • P350

The P3-35 features digital and analog inputs, Bluetooth® functionality (so you can stream content right from your smart phone), IR learning (so you can program your television remote to control the amp's volume), and even a line-level subwoofer output option, allowing you to integrate any powered subwoofer into your set-up. The P3-35 even features Dolby Digital® decoding, ensuring that you'll never lose the surround content in any Dolby Digital mixes.

The P3-35 amp measures only 1 ¼" by 4", so its small enough to fit behind a wall mounted TV and, when paired with any of Phase Technology's ultra-thin Teatro speakers, will create the perfect installation scenario for this powerful and feature-rich mini-amplifier.

The PhaseTech P350 amplifier was designed for maximum versatility in amplification. With a massive toroidal transformer and a Class "G" design. It balances power and efficiency into an audiophile class amplifier. The P350 is the companion amplifier to Phase Technology custom in-wall subwoofer systems yet it also has the flexibility of operation as a full range high current, high performance, mono-block audio power amplifier.

The P350 amp features an adjustable bass EQ, sub filter in/out switch, switchable low pass crossover, a level control for matching your subwoofer system to the main loudspeakers and phase control for matching the output phase to that of your speakers.



P3-35

Description: 3-Channel Amplifier
Inputs: Stereo Mini Analog, Optical Digital, Bluetooth®
Outputs: 2 or 3 Channel Euroblock; Line Level Sub Out
Frequency Response: 10 Hz - 20 kHz +/-5 dB @ 1 Watt RMS 8Ω >1% THD
Frequency EQ: +3 dB Switchable @ 120, 2 kHz, 8 kHz
Amplifier Power: 2 Channel - 50 Watts RMS/CH >1% @ 8Ω, 55 Watts @ 4Ω 3 Channel - 35 Watts RMS/CH >1% @ 8Ω, 40 Watts @ 4Ω
Dimensions: 1.25" H x 3.9" W x 7.25" D
Weight: 0.93 lbs.



P350

Description: Class-G High Current Subwoofer/Full-Range Monoblock Amplifier
Inputs: (1x) Gold-Plated Balanced RCA; (1x) Balanced XLR
Crossover Frequency: Low Pass 40 - 120 Hz Adjustable @ 24 dB/Octave
LFE Frequency Response: 20 - 500 Hz
Full-Range Frequency (± .25 dB): 10 Hz - 20 kHz
Low Frequency EQ: -3 dB to +6 dB @ 30 Hz
Max Current Consumption: 3 Amps @ 8Ω, 5.5 Amps @ 4Ω Continuous
Amplifier Power: 350 W RMS @ 4Ω, 700 W Peak; 225 W RMS @ 8Ω, 400 W Peak
Dimensions: 2" H x 17.25" W x 13.25" D
Weight: 17 lbs.
Protection Features: Soft Clipping (Subwoofer Mode), Short Circuit Overload, Thermostatic Variable Speed Fan Cooling, Thermal Overload Protection, Transformer Thermal Protection, Over-Current Protection